



Office

INVESTOR IN PEOPLE

GB 99/00469

**PRIORITY
DOCUMENT**

SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

The Patent Office
Concept House
Cardiff Road
Newport

South Wales
NP9 1PD 15 APR 1999

WIPO PCT

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.


In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.

Signed

Dated

11/3/99



17FEB98 E338881-16 002246
 P01/7700 25.00 - 9803273.3

The Patent Office

Cardiff Road
 Newport
 Gwent NP9 1RH

Request for a grant of a patent

(Notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

1. Your name

P/4127.GB JAT

2. Patent application number

(The Patent Office will fill in this part)

9803273.3

16 FEB 1998

3. Full name, address and postcode of the or of each applicant
(underline all surnames)

UNIVERSITY OF SURREY
 GUILDFORD
 SURREY GU2 5XH
 UNITED KINGDOM

Patents ADP number (if you know it)

If the applicant is a corporate body, give the country/state of its incorporation

UNITED KINGDOM

798512001

4. Title of the invention

ADAPTIVE MULTIFILAR ANTENNA

5. Name of your agent (if you have one)

"Address for service" in the United Kingdom to which all correspondence should be sent
(including the postcode)

D YOUNG & CO
 21 NEW FETTER LANE
 LONDON
 EC4A 1DA

MATHISEN, MACARA & CO
 THE COACH HOUSE
 6-8 SWAKELEY'S ROAD
 ICKENHAM
 UXBIDGE
 MIDDLESEX UB8 3BZ

Patents ADP number (if you have one)

59006

6. If you are declaring priority from one or more earlier patent applications, give the country and date of filing of the or each of these earlier applications and (if you know it) the or each application number

Country

Priority application
 number
 (if you know it)

Date of filing
 (day/month/year)

7. If this application is divided or otherwise derived from an earlier UK application, give the number and filing date of the earlier application

Number of earlier
 application

Date of filing
 (day/month/year)

8. Is a statement of inventorship and of right to grant of a patent required in support of this request? **YES**
over 'Yes' if:
a) any applicant named in part 3 is not an inventor, or
b) there is an inventor who is not named as an applicant, or
c) any named applicant is a corporate body.
See note (d))

9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document

Continuation sheets of this form 0

Description 6

Claims(s) 3 *SR*

Abstract 1

Drawing(s) 3

10. If you are also filing any of the following, state how many against each item.

Priority documents

Translations of priority documents

Statement of inventorship and right to grant of a patent (Patents Form 7/77)

Request for preliminary examination and search (Patents Form 9/77)

Request for substantive examination (Patents Form 10/77)

Any other documents (please specify)

11. I/We request the grant of a patent on the basis of this application.

Signature

Date

D Young & Co

13 02 98

D YOUNG & CO

Agents for the Applicants

12. Name and daytime telephone number of the person to contact in the United Kingdom

J A TURNER

01703 634816

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

a) If you need help to fill in this form or you have any questions, please contact the Patent Office on 01645 500505

b) Write your answers in capital letters using black ink or you may type them

c) If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.

d) If you answered 'Yes' Patents Form 7/77 will need to be filed.

e) Once you have filled in the form you must remember to sign and date it.

f) For details of the fee and ways to pay please contact the Patent Office.

ADAPTIVE MULTIFILAR ANTENNA

This invention relates to adaptive multifilar antennas.

5 In fields such as mobile telephony and communication, it is being proposed that radio frequency transceivers operating in different frequency bands, and providing different services, should be integrated into single consumer devices.

For example, in order to improve the coverage area in which a mobile telephone can be used, a satellite system transceiver, a terrestrial transceiver and a domestic cordless telephone transceiver might be integrated into one hand-held unit.
10 An alternative example is a dual service telephone operating at 1800MHz in the user's home country but having the capability of operating at 900MHz in other countries under a so-called roaming arrangement.

The electronics needed to achieve this aim are rapidly becoming smaller and lighter. A remaining problem area for multi-frequency, multi-system operation,
15 however, is the antenna.

In order to operate as described above, an antenna should be able to work at different frequencies and with different types of base station. For example, one service may use terrestrial base stations and another may use orbiting satellites. This means that if the handset antenna is typically used in a vertical position (with the
20 handset held next to the user's head) then for one service the antenna should have a radiation pattern substantially omnidirectional in azimuth and for the other service it should have an approximately hemispherical radiation pattern.

To cater for the different pattern and frequencies in use, it has been proposed to employ two distinct antennas within a common volute.

25 This invention provides a multifilar antenna comprising:

n spaced antenna filaments, where n is an integer greater than 1;

a matching circuit for matching the characteristic impedance of the antenna to that of a transmitting and/or receiving apparatus;

a phasing circuit for applying respective gain and phase adjustments to signals
30 passed to or from the n filaments;

switch means associated with each filament for selectively altering the electrical length and/or interconnections of the filaments;

means for detecting electrical properties of the multifilar antenna with respect to the frequency, polarisation and/or direction of propagation of a signal to be received or transmitted by the multifilar antenna and/or impedance matching of the antenna; and

5 control means, responsive to the detecting means, for controlling the operation of the matching circuit, the phasing circuit and the switch means to adjust the properties of the multifilar antenna to suit better a current signal to be received or transmitted.

10 In the invention, the phase and gain relationships for signals from individual filaments of a multifilar antenna, along with the electrical length and interconnection pattern of the filaments, can be varied automatically in order to improve (or possibly to optimise, within the resolution of the adjustment system) the properties of the antenna for a particular signal to be received or transmitted.

15 For example, in embodiments of the invention the above parameters could be varied to provide the best received signal level, the best signal to noise ratio, or the best signal to (noise plus interference) ratio and/or the best VSWR.

20 The adjustments will generally lead to a change in the antenna's frequency response and radiation pattern (shape and polarisation). In fact, it does not matter to the adjustment system what that change is quantitatively; the system simply makes adjustments so as to improve the handling of the current signal.

The invention will now be described by way of example with reference to the accompanying drawings, throughout which like parts are referred to by like references, and in which:

25 Figure 1 is a schematic diagram of a quadrifilar antenna;
Figure 2 is a schematic diagram of an antenna interface circuit; and
Figure 3 is a more detailed schematic diagram of one possible implementation of the antenna system of Figure 2.

Figure 1 is a schematic diagram of a quadrifilar helical antenna (QHA).

30 The QHA comprises four helical elements 10..40 and eight radial elements 50..120. (In other embodiments six angularly spaced helical elements could be used).

The helical elements are intertwined as shown in Figure 1, and are disposed about a longitudinal axis of the antenna by 90° with respect to one another. Four of

the radials 50..80 are disposed on the top and four 90..120 on the bottom of the volute, connecting the helical elements and forming two bifilar loops. The antenna is fed on one set of radials 90,110, with 90° phase difference between the two feeds.

The radials 50..80 at the top end of the antenna with respect to the feed (which in this example are at the bottom) may be shorted in pairs or may be open-circuit depending on the resonant length of the helical elements and the required response.

The QHA is described in the following references:

- [1] Kilgus C.C., "Multielement, Fractional Turn Helices", IEEE Transactions on Antenna and Propagation, Vol.AP-16, pp. 499-500, July 1968
- [2] Kilgus C.C., "Resonant Quadrifilar Helix", IEEE Transactions on Antenna and Propagation, Vol.AP-17, pp. 349-351, May 1969
- [3] Kilgus C.C., "Resonant Quadrifilar Helix Design", The Microwave Journal, December 1970.

The antenna's radiation pattern mode (hemispherical or other) depends on the phase combination used on the two or four feeds. The exact shape of the antenna's radiation pattern in each mode depends on the pitch and dimensions of the helices. In the axial mode it has a shape varying from hemispherical to cardioid depending on the dimensions of the structure. The polarisation is circular with a very good axial ratio inside the 3dB angle.

In other embodiments, the multifilar antenna arrangement can also be used for diversity purposes. The different filaments can be used to provide space diversity between uncorrelated received signals. The effect of weighting the gain and phase can affect both the shape and the polarisation of the radiation pattern. This effect can benefit the transceiver in two ways. Firstly, the pattern shape and the polarisation are matching the direction and the polarisation of the incoming signal to try to optimise or improve the criterion ratio (S/N or $S/(N+I)$), and secondly the structure can be used for polarisation diversity using the resulting pattern of different filaments or pairs of filaments.

Figure 2 is a schematic diagram of an antenna system comprising an adapted QHA 200 and an antenna interface circuit.

In Figure 2, the four elements of the QHA 200 are connected separately to an

adaptive matching circuit 210. (In the configuration shown in Figure 1, the antenna is in a receive mode, but it will be clear that signals could instead be supplied to the antenna, in a transmit mode, by reversing the direction of signal propagation arrows in Figure 2.) The adaptive matching circuit 210 is under the control of a matching controller 220, which in turn is responsive to a system controller 230.

Received signals from the adaptive matching circuit are supplied to four respective variable weighting circuits W1..W4. Each of W1..W4 comprises a variable gain stage and a variable phase delay, all controllable by the system controller 230.

The outputs of the four variable weighting elements W1..W4 are combined by an adder/weight combiner 240 to form a composite signal. This composite signal is then stored 250. A sensor 280 examines the signal (e.g. the level of the signal to (noise plus interference) ratio) and passes this information to the controller which in turn adjusts the weighting factors of the weighting elements W1..W4, the matching circuit 210 and the switch elements 290, 300 to improve or possibly optimise the parameter sensed by the sensor 280. The optimisation information can be used to optimise or improve the quality of the stored signal, which is then passed to the demodulator 260. The information is also used to adjust the antenna system to receive the next incoming signal.

In each element of the QHA, there is a switch 290 capable of isolating a portion of the element remote from the feed point. The switch could be, for example, a PIN diode switch. Similarly, a switch 300 is capable of shorting or isolating pairs of the elements at the end remote from the feed point.

The operations performed by the switches 290 and 300, under the control of a switch controller 310, can change the response and radiation pattern of the antenna. In particular, by isolating a section of each element, the electrical length of the elements is made shorter and so the frequency of operation will be higher. Again, these operations are carried out under the control of the system controller to improve or possibly optimise operation with a particular signal frequency, polarisation and direction of propagation.

Figure 3 is a more detailed schematic diagram of one possible implementation of the antenna system of Figure 2, which also shows operation to improve or optimise

the VSWR during a transmission operation and $S/N+I$ during a receive mode. (Incidentally, when $S/N+I$ is improved by adapting the antenna matching in a receive mode, this has an indirect side-effect of tending to improve the VSWR. Also, when the pattern mode, polarisation and direction are improved by adjusting for the best or an improved $S/N+I$, this similarly has a corresponding improving effect in a transmit mode.)

In Figure 3, the operation of the weighting elements $W1..W4$ is carried out in a digital domain, as is the operation of the adder/weight combiner 240.

The output of the adaptive matching circuit 210 is supplied to a quadrature downconverter 400 comprising an intermediate stage 410 where a local oscillator signal is mixed with the radio frequency signal, an amplifier 420 and a further stage of mixing with a local oscillator signal with a 0° and 90° phase relationship to generate two demodulated outputs I and Q. These are both converted to digital representations by A/D converters 430 before being stored in a RAM 440. This process is replicated for each of the filaments of the QHA. Similarly, for the transmit side, an output from the RAM 440 is passed to a quadrature modulator 450 before being routed via the adaptive matching circuit 210 to the respective antenna filaments. A VSWR detector 460 operates in a transmit and/or receive mode to detect the standing wave ratio of the antennas. The output of this is stored in the RAM 440.

The RAM is connected to a digital signal processing (DSP) unit 470 which combines the digital representations of the signals stored in the RAM 440 in respective proportions and using respective phases (i.e. performs the operation of the weighting blocks $W1..W4$), detects and optimises the selected parameter such as signal-to-noise ratio, sends control signals to the adaptive matching circuits to change from one frequency band to another or to overcome de-tuning effects, and also controls the switch controller 310 and in turn the switches 290,300 within the helical elements.

One appropriate DSP algorithm is for the transmitter to send packet header, reference or training symbols, which are known to the receiver. Any disturbance to the received signals during the reception of the training symbols is a measure of $N+I$ and can be reduced by trial and error (repeated combining of the digital

representations stored in the RAM 440), direct matrix inversion of the associated correlation matrix or by iteration approaches such as so-called LMS or RLS algorithms. However, even if known training symbols are not available, a measure of the disturbance to the signal can be made by error detection algorithms applied to the received symbols.

CLAIMS

1. An adaptive multifilar antenna comprising:
n spaced antenna filaments, where n is an integer greater than 1;
5 a matching circuit for matching the characteristic impedance of the antenna to that of a transmitting and/or receiving apparatus;
a phasing circuit for applying respective gain and phase adjustments to signals passed to or from the n filaments;
switch means associated with each filament for selectively altering the
10 electrical length and/or interconnections of the filaments;
means for detecting electrical properties of the multifilar antenna with respect to the frequency, polarisation and/or direction of propagation of a signal to be received or transmitted by the multifilar antenna and/or impedance matching of the antenna; and
15 control means, responsive to the detecting means, for controlling the operation of the matching circuit, the phasing circuit and the switch means to adjust the properties of the multifilar antenna to suit better a current signal to be received or transmitted.
- 20 2. An antenna according to claim 1, in which:
signal connections to/from the filaments are at a first end of each filament;
and
the switch means is operable to selectively interconnect pairs of filaments at
a second end of those filaments remote from the first end.
- 25 3. An antenna according to claim 1 or claim 2, in which:
each filament comprises at least a first filament section and a second filament section; and
the switch means is operable to selectively connect or isolate the first and
30 second filament sections of each filament so as to vary the electrical length of that filament.

4. An antenna according to any one of the preceding claims, in which:
the detecting means is operable to detect a signal to noise ratio of a received signal; and
the control means is operable to control the operation of the matching circuit
5 and the switch means so as to improve the signal to noise ratio of the received signal.
5. An antenna according to any one of claims 1 to 4, in which:
the detecting means is operable to detect a signal to (noise plus interference)
ratio of a received signal; and
10 the control means is operable to control the operation of the matching circuit
and the switch means so as to improve the signal to (noise plus interference) ratio of
the received signal.
6. An antenna according to any one of claims 1 to 4, in which:
15 the detecting means is operable to detect a signal level of a received signal;
and
the control means is operable to control the operation of the matching circuit
and the switch means so as to improve the signal level of the received signal.
- 20 7. An antenna according to any one of claims 1 to 4, in which:
the detecting means is operable to detect a VSWR for a transmitted signal; and
the control means is operable to control the operation of the matching circuit
and the switch means so as to improve the VSWR for transmission of that signal.
- 25 8. An antenna according to any one of the preceding claims, in which the
detecting means comprises:
analogue to digital conversion means for converting respective signals received
by the filaments into corresponding digital representations;
a memory for storing the digital representations;
30 means for combining the digital representations using respective phase
relationships and gains; and
means for detecting properties of the antenna by analysis of the combined

digital representations.

9. An antenna according to any one of the preceding claims, in which the detecting means operates at least during reception of a reference signal burst by the antenna.

5

10. An antenna according to any one of the preceding claims, in which n is an even integer.

10

11. An antenna according to any one of the preceding claims, in which n is equal to 4 or 6.

12. An antenna according to any one of the preceding claims, in which the filaments are helically shaped.

15

13. An antenna according to any one of the preceding claims, in which the filaments are at least partially intertwined.

20

14. A multifilar antenna substantially as hereinbefore described with reference to the accompanying drawings.

ABSTRACTADAPTIVE MULTIFILAR ANTENNA

5 A multifilar antenna comprises n spaced antenna filaments, where n is an integer greater than 1; a matching circuit for matching the characteristic impedance of the antenna to that of a transmitting and/or receiving apparatus; a phasing circuit for applying respective gain and phase adjustments to signals passed to or from the n filaments; switch means associated with each filament for selectively altering the
10 electrical length and/or interconnections of the filaments; means for detecting electrical properties of the multifilar antenna with respect to the frequency, polarisation and/or direction of propagation of a signal to be received or transmitted by the multifilar antenna and/or impedance matching of the antenna; and control means, responsive to the detecting means, for controlling the operation of the
15 matching circuit, the phasing circuit and the switch means to adjust the properties of the multifilar antenna to suit better a current signal to be received or transmitted.

Figure 2




Fig. 1




Figure 2




Fig 3